

■ Detectors of Temperature Setting Type

■ Detectors of Temperature Setting Type

▶ Description

Micom ways used, and the temperature displayed by the PT-1000Ω Sensor, the user can arbitrary set a the set temperature.

External communication is an excellent product that can transmit real-time temperature handcuffs through the RS-485

CE Certified



▶ Features

- Using a Micro Processor and PT1000Ω designed to measure the temperature at the exactly to -30 °C 300 °C.
- The user sets the temperature value of primary, secondary drive enhanced stability and accuracy were divided, The users can easily adjust the temperature by using the Setting Switch Key
- When the fire signal occurs, even when the power is re-applied the power OFF to keep the fire signal in case of fire enhancing the accuracy of the post-judgment
- To determine the presence of error PT1000Ω sensor part for measuring the temperature Err on the front panel (Open, Short) and break the amber LED is lit, and Self-diagnostic function that beeps
- Using the RS-485 communication and monitoring system by connecting the respective circumstances of the Controller General Dispatch state can be easily confirmed

SPECIFICATION

Model	NTD-1GG0242
Size (W x D x H / mm)	110 x 105 x 40
Weight	0.3kg
Set Temperature	-30°C ~ 300°C
Apply Sensor	PT 1000Ω
Use Temperature	-10°C ~ 50°C
Current Consumption	Standby-70mA / Operation-160mA